

CA ACF2 15.0
CA RS 1507 Service List

Release	Service	Description	Type
15.0	RO77363	S0C9 SAFOEGRP+1AA	PTF
	RO79272	S0C2 IN ACF79DBQ AT ACF2 SHUTDOWN	PTF
	RO79494	HELP COMMAND FOR ACF2 MODIFY IS INCOMPLETE AND GETS ACF67001	PTF
	RO80499	CLEANUP CALLED FOR NON-SIGNON RACROUTE EXTRACT	PTF
	RO81258	ADD INTERNAL CLASMAP RECORD REQUIRED BY OTHER CA PRODUCT	PTF
	RO81813	OVERLAY OR S0C4 ABEND IN ACF04RSI COPYING DB2 SECONDARY IDS	*HIP/PRP*
	RO82437	ACF2 INIT ABEND S0C4 IN ACF04RSD WITH RO70670	*HIP/PRP*
The CA RS 1507 service count for this release is 7			

CA ACF2
CA RS 1507 Service List for CAX1F00

FMID	Service	Description	Type
CAX1F00	RO77363	S0C9 SAFOEGRP+1AA	PTF
	RO79272	S0C2 IN ACF79DBQ AT ACF2 SHUTDOWN	PTF
	RO79494	HELP COMMAND FOR ACF2 MODIFY IS INCOMPLETE AND GETS ACF67001	PTF
	RO80499	CLEANUP CALLED FOR NON-SIGNON RACROUTE EXTRACT	PTF
	RO81258	ADD INTERNAL CLASMAP RECORD REQUIRED BY OTHER CA PRODUCT	PTF
	RO81813	OVERLAY OR S0C4 ABEND IN ACF04RSI COPYING DB2 SECONDARY IDS	*HIP/PRP*
	RO82437	ACF2 INIT ABEND S0C4 IN ACF04RSD WITH RO70670	*HIP/PRP*
The CA RS 1507 service count for this FMID is 7			

CA ACF2 15.0
CA RS 1507 - PTF RO77363 Details

Release	Service	Details
15.0	RO77363	<p>RO77363 M.C.S. ENTRIES = ++PTF (RO77363)</p> <p>S0C9 SAFOEGRP+1AA</p> <p>PROBLEM DESCRIPTION: Possible S0C9 in SAFOEGRP+1AC attempting to determine if the user represented by the input ACEE has access to the group represented by the input GID.</p> <p>SYMPTOMS: OMVS process terminates with abend.</p> <p>IMPACT: Possibly unable to access OMVS services.</p> <p>CIRCUMVENTION: None.</p> <p>PRODUCT(S) AFFECTED: CA-ACF2-MVS Release 15.0</p> <p>Related Problem: ACF2MS 9718</p> <p>Copyright (C) 2015 CA. All rights reserved. R01167-ACF150-SP1</p> <p>DESC(S0C9 SAFOEGRP+1AA). ++VER (Z038) FMID (CAX1F00) PRE (RO45571 RO54826 RO70670) SUP (RO62525 TR62525 TR77363) ++HOLD (RO77363) SYSTEM FMID(CAX1F00) REASON (DYNACT) DATE (15160) COMMENT (</p> <pre> +-----+ CA-ACF2-MVS Release 15.0 +-----+ SEQUENCE After Apply +-----+ PURPOSE Activate change +-----+ USERS All users AFFECTED +-----+ KNOWLEDGE Operator commands REQUIRED +-----+ ACCESS z/OS Operator console REQUIRED +-----+ ***** * STEPS TO PERFORM * ***** 1. LLA Refresh 2. F ACF2,NEWMOD(SAFOEDRV)). </pre>

CA ACF2 15.0
CA RS 1507 - PTF RO79272 Details

Release	Service	Details
15.0	RO79272	<p>RO79272 M.C.S. ENTRIES = ++PTF (RO79272)</p> <p>S0C2 IN ACF79DBQ AT ACF2 SHUTDOWN PROBLEM DESCRIPTION: During ACF2 shutdown it is possible to get message ACF8A016 ACFMAIN UNABLE TO ACQUIRE CLUSTERS - CLOSEDOWN CONTINUING followed by an 0C2 abend in ACF79DBQ. If we cannot get exclusive control of one of the databases we will wait 5 seconds and try again. If we still cannot get the enqueue we will put out the informational message and due to being in the wrong mode we abend trying to continue with the shutdown. This apar will do 2 things. Correct the code so we are in the correct mode if this situation should ever occur again. The second part of the update adds to the logic to close the window in which we cannot get the enqueue on our databases at shutdown. SYMPTOMS: ACF8A016 ACFMAIN UNABLE TO ACQUIRE CLUSTERS - CLOSEDOWN CONTINUING CCSR010E MAINRECV S0C2 at 00030C7A LMOD ACF8AMA0 CSECT ACF79DBQ +0000FA ACF2 N/A ACF2 IMPACT: None, ACF2 continues to shutdown. CIRCUMVENTION: None PRODUCT(S) AFFECTED: CA-ACF2-MVS Release 15.0 Related Problem: ACF2MS 9739 Copyright (C) 2015 CA. All rights reserved. R01189-ACF150-SP1</p> <p>DESC(S0C2 IN ACF79DBQ AT ACF2 SHUTDOWN). ++VER (Z038) FMID (CAX1F00) PRE (RO27471 RO30324 RO33981 RO36462 RO36896 RO41317 RO52747 RO54836 RO65813 RO71831) SUP (RO20617 RO59280 TR20617 TR54581 TR54838 TR59278 TR59280 TR79272) ++HOLD (RO79272) SYSTEM FMID(CAX1F00) REASON (DYNACT) DATE (15167) COMMENT (</p> <pre> +-----+ CA-ACF2-MVS Release 15.0 +-----+ SEQUENCE After Apply +-----+ PURPOSE Activate change without IPL +-----+ USERS All users AFFECTED +-----+ KNOWLEDGE Operator commands REQUIRED +-----+ ACCESS z/OS Operator console REQUIRED +-----+ ***** * STEPS TO PERFORM * ***** 1. LLA Refresh 2. Restart ACF2). </pre>

CA ACF2 15.0
CA RS 1507 - PTF RO79494 Details

Release	Service	Details
15.0	RO79494	<p>RO79494 M.C.S. ENTRIES = ++PTF (RO79494)</p> <p>HELP COMMAND FOR ACF2 MODIFY IS INCOMPLETE AND GETS ACF67001 PROBLEM DESCRIPTION: The help panels incorrectly specify 'F ACF2' as a subcommand that can be specified for help. This should be 'F'. When doing a 'HELP F': The syntax section is missing the 'F ACF2,NEWUID' command. The NEWXREF command is missing the ROL type code. The REBUILD command is missing the DIVISION parameter. SYMPTOMS: help f acf2 ACF67001 COMMAND ACF2 INVALID OR AMBIGUOUS IMPACT: None CIRCUMVENTION: None PRODUCT(S) AFFECTED: CA-ACF2-MVS Release 15.0 Related Problem: ACF2MS 9751 Copyright (C) 2015 CA. All rights reserved. R01192-ACF150-SP1</p> <p>DESC(HELP COMMAND FOR ACF2 MODIFY IS INCOMPLETE AND GETS ACF67001). ++VER (Z038) FMID (CAX1F00) PRE (RO32183 RO60483 RO60522) SUP (TR60423 TR79494)</p>

CA ACF2 15.0
CA RS 1507 - PTF RO80499 Details

Release	Service	Details
15.0	RO80499	<p>RO80499 M.C.S. ENTRIES = ++PTF (RO80499)</p> <p>CLEANUP CALLED FOR NON-SIGNON RACROUTE EXTRACT</p> <p>PROBLEM DESCRIPTION: CA ACF2 for z/OS erroneously calls CA Cleanup for ACF2 to mark a LOGONID as referenced during RACROUTE REQUEST=EXTRACT processing.</p> <p>SYMPTOMS: Incorrect LOGONID reference date in SYSPRINT file of AT6#RPT.</p> <p>IMPACT: Nonspecific depending on client use.</p> <p>CIRCUMVENTION: None</p> <p>Related Problem: ACF2MS 9762</p> <p>Copyright (C) 2015 CA. All rights reserved. R01199-ACF150-SP1</p> <p>DESC(CLEANUP CALLED FOR NON-SIGNON RACROUTE EXTRACT). ++VER (Z038) FMID (CAX1F00) SUP (TR80499) ++HOLD (RO80499) SYSTEM FMID(CAX1F00) REASON (DYNACT) DATE (15160) COMMENT (</p> <pre> +-----+ CA-ACF2-MVS Release 15.0 +-----+ SEQUENCE After Apply +-----+ PURPOSE Enable updated code +-----+ USERS All users AFFECTED +-----+ KNOWLEDGE Console commands REQUIRED +-----+ ACCESS Console commands REQUIRED +-----+ ***** * STEPS TO PERFORM * ***** 1. Perform an LLA REFRESH 2. Issue console command: F ACF2,NEWMOD(ACF00SVA)). </pre>

CA ACF2 15.0
CA RS 1507 - PTF RO81258 Details

Release	Service	Details
15.0	RO81258	<pre> RO81258 M.C.S. ENTRIES = ++PTF (RO81258) ADD INTERNAL CLASMAP RECORD REQUIRED BY OTHER CA PRODUCT PROBLEM DESCRIPTION: This apar defines a new internal clasmap record as requested by another CA product. SYMPTOMS: None IMPACT: None CIRCUMVENTION: A site could do the following command in the ACF command: SET CONTROL(GSO) INSERT CLASMAP.CADCD RESOURCE(CADCD) RSRCTYPE(DCD) ENTITYLN(255) PRODUCT(S) AFFECTED: CA-ACF2-MVS Release 15.0 CA-ACF2-MVS Release 16.0 Related Problem: ACF2MS 9671 Copyright (C) 2015 CA. All rights reserved. R01201-ACF150-SP1 DESC(ADD INTERNAL CLASMAP RECORD REQUIRED BY OTHER CA PRODUCT). ++VER (Z038) FMID (CAX1F00) PRE (RO35100 RO45722 RO61510 RO62686) SUP (AR24613 RO20460 RO24613 RO24618 RO27574 RO38222 RO42223 RO54052 RO69921 TR20460 TR24613 TR24617 TR24618 TR27574 TR38222 TR42223 TR54031 TR54052 TR69921 TR71633 TR81258) ++HOLD (RO81258) SYSTEM FMID(CAX1F00) REASON (IPL) DATE (15162) COMMENT (+-----+ CA-ACF2-MVS Release 15.0 +-----+-----+ SEQUENCE After Apply +-----+-----+ PURPOSE Activate change +-----+-----+ USERS All users AFFECTED +-----+-----+ KNOWLEDGE Operator commands REQUIRED +-----+-----+ ACCESS z/OS Operator console REQUIRED +-----+-----+ ***** * STEPS TO PERFORM * ***** IPL with CLPA).</pre>

CA ACF2 15.0
CA RS 1507 - PTF RO81813 Details

Release	Service	Details
15.0	RO81813	<p>RO81813 M.C.S. ENTRIES = ++PTF (RO81813)</p> <p>OVERLAY OR SOC4 ABEND IN ACF04RSI COPYING DB2 SECONDARY IDS PROBLEM DESCRIPTION: There is the possibility of either an overlay or abend SOC4 in ACF04RSI with the ACF2 DB2 interface. This happens when we get garbage passed to the ACF2 DB2 interface for a secondary id list. There is no way to tell what the overlay could be. We will take the garbage passed to us and attempt to use it to copy the list of secondary ids to the smf record for reporting in the ACFRPTRV report. SYMPTOMS: Reported as the following message but it would depend upon what was overlaid or if we ran into a page of storage that was not allocated and got an OC4 trying to write data to that page. COMPON=VSM- GETMAIN,COMPID=SC1CH,ISSUER=IGVRSRTN,ABEND=OC4 IMPACT: Depends upon what was overlaid. CIRCUMVENTION: None PRODUCT(S) AFFECTED: CA-ACF2-MVS Release 15.0 Related Problem: ACF2MS 9777 Copyright (C) 2015 CA. All rights reserved. R01205-ACF150-SP1</p> <p>DESC(OVERLAY OR SOC4 ABEND IN ACF04RSI COPYING DB2 SECONDARY IDS). ++VER (Z038) FMID (CAX1F00) PRE (RO45722 RO64343) SUP (IC55970 TR81813) ++HOLD (RO81813) SYSTEM FMID(CAX1F00) REASON (DYNACT) DATE (15169) COMMENT (</p> <pre> +-----+ CA-ACF2-MVS Release 15.0 +-----+ SEQUENCE After Apply +-----+ PURPOSE Activate change without IPL +-----+ USERS All users AFFECTED +-----+ KNOWLEDGE Operator commands REQUIRED +-----+ ACCESS z/OS Operator console REQUIRED +-----+ ***** * STEPS TO PERFORM * ***** 1. F LLA,REFRESH 2. F ACF2,NEWMOD(ACF00SVA)). </pre>

CA ACF2 15.0
CA RS 1507 - PTF RO82437 Details

Release	Service	Details
15.0	RO82437	<p>RO82437 M.C.S. ENTRIES = ++PTF (RO82437)</p> <p>ACF2 INIT ABEND S0C4 IN ACF04RSD WITH RO70670</p> <p>PROBLEM DESCRIPTION: An error in GETMAIN return code checking may lead to S0C4 abends in ACF04RSD at offsets x'14C6', x'196', and x'3E6'. The S0C4 abends are caused by RO70760 but may also occur if you have correcting PTFs RO76805 or RO78287 applied.</p> <p>This problem has been observed in two environments so far: 1) Sites that apply z/OS 2.1 RSU 1505 2) Sites that apply maintenance for z13 support</p> <p>*** This PTF addresses PRODUCT ERROR ALERT (PEA) RI82466 ***</p> <p>SYMPTOMS: SVC dump and messages beginning with: CCSR010E ACF04RSD S0C4 at aaaaaaaaa LMOD ACF00SVA CSECT ACF04RSD and may include: ACFFE001 ACF04RSD DUMP IN PROGRESS</p> <p>IMPACT: ACF2 may not initialize.</p> <p>CIRCUMVENTION: None.</p> <p>PRODUCTS AFFECTED: CA ACF2 FOR Z/OS Release 15.0 CA ACF2 FOR Z/OS Release 16.0</p> <p>Related Problem: ACF2MS 9784</p> <p>Copyright (C) 2015 CA. All rights reserved. R01211-ACF150-SP1</p> <p>DESC(ACF2 INIT ABEND S0C4 IN ACF04RSD WITH RO70670). ++VER (Z038) FMID (CAX1F00) PRE (RO70670) SUP (JC55970 RI82466 RO24029 RO68549 TR24029 TR68549 TR82437) ++HOLD (RO82437) SYSTEM FMID(CAX1F00) REASON (DYNACT) DATE (15180) COMMENT (</p> <pre> +-----+ CA-ACF2-MVS Release 15.0 +-----+-----+ SEQUENCE After Apply +-----+-----+ PURPOSE Make new code available +-----+-----+ USERS All users AFFECTED +-----+-----+ KNOWLEDGE Linklist contents REQUIRED Console commands +-----+-----+ ACCESS Master console REQUIRED +-----+-----+ ***** * STEPS TO PERFORM * ***** 1. Perform an LLA REFRESH 2. Issue console command: F ACF2,NEWMOD(ACF00SVA)). </pre>